

RC-1572MKII

STEREO PREAMPLIFIER



ROON
TESTED

Certified
Roon Tested



Supports MQA and
MQA Studio



Balanced XLR
inputs and outputs



Moving Magnet
Phono input for
turntable connection



Wireless
aptX™ and AAC
Bluetooth



Texas Instruments
premium 32-bit/384kHz
Digital to Analog Converter

Affordable high-end begins with Rotel's RC-1572MKII Preamplifier including multiple acoustic upgrades and refinements processing your favorite analog and digital sources to an even higher level of performance in stunning clarity with a natural, enveloping sound stage.

As an essential component in a Hi-Fi audio stack the RC-1572MKII's precision engineering begins with Rotel's ultra-low noise power supply including a large, in-house manufactured toroidal transformer. The transformer design reduces stray radiated emissions and feeds a bank of slit-foil, low ESR capacitors delivering stable current to all sensitive circuits reducing noise and distortion with an ultra-quiet noise floor.

A premium Texas Instruments 32-bit Digital to Analog converter (DAC) renders the digital sources supported by custom tuned, proprietary external output filters ensuring the audio is effortlessly presented with exceptional dynamic detail and musical expression.

Analog, Digital, XLR, aptX™ and AAC Wireless Bluetooth and Moving Magnet Phono Stage inputs ensure connection to your favorite music sources. Digital media files are supported via a 32-bit/384kHz PC-USB connection supporting MQA and is fully certified Roon Tested for graceful access to the near limitless catalog of online music.

The RC-1572MKII is easy to operate using the included remote control and front panel display. Automatic power controls, signal sensing, fixed volume settings and tone adjustments optimize customization settings.

RCA, XLR and subwoofer outputs are provided for installation flexibility. Ethernet and RS232 ensure simple integration with control systems and software updates.

Bring your CD's, Digital Files and Vinyl allowing the RC-1572MKII to bridge generations of music and music lovers.

RC-1572MKII

STEREO PREAMPLIFIER



SPECIFICATIONS

Total Harmonic Distortion (20 Hz-20k Hz)	< 0.004%	Digital Section	
Intermodulation Distortion (60 Hz : 7k Hz, 4:1)	< 0.004%	Frequency Response	20 Hz - 20k Hz (0 ± 0.5 dB, Max)
Input Sensitivity / Impedance		Signal to Noise Ratio (IHF "A" weighted)	100 dB
Phono Input (MM)	3 mV / 47k ohms	Input Sensitivity/Impedance	0 dBFs / 75 ohms
Line Level Inputs (RCA)	200 mV / 100k ohms	Preamplifier Output Level	1.44 V (at - 20 dB)
Line Level Inputs (XLR)	300 mV / 100k ohms	Coaxial/Optical Digital Signals	SPDIF LPCM (up to 24-bit / 192k Hz)
Input Overload		PC-USB	USB Audio Class 1.0 (up to 24-bit / 96k Hz) USB Audio Class 2.0 (up to 32-bit / 384k Hz)* *Driver installation required
Phono Input	63 mV		MQA and MQA Studio (up to 24-bit / 384k Hz)
Line Level Inputs (RCA)	4 V		Roon Tested
Line Level Inputs (XLR)	5 V		
Output Level		Power Requirements	
Line Level (RCA)	1 V	Europe	230 V, 50 Hz
Balance (XLR)	2 V	USA	120 V, 60 Hz
Frequency Response		Power Consumption	35 watts
Phono Input	20 Hz-20k Hz (+0.3 dB, -0.2 dB)	Standby Power Consumption	
Line Level Inputs (RCA)	10 Hz-100k Hz (+0 dB, -0.2 dB)	Normal	< 0.5 watts
Line Level Inputs (XLR)	10 Hz-100k Hz (+0 dB, -0.2 dB)	Network Wakeup	< 2 watts
Tone Controls		BTU (4 ohms, 1/8 power)	65 BTU/h
Bass	±10 dB at 100 Hz	Dimensions (W x H x D)	431 x 99 x 338 mm 17 x 3 7/8 x 13 1/4 in
Treble	±10 dB at 10k Hz	Front Panel Height	2U / 88.1mm / 3 1/2 in
Signal to Noise Ratio (IHF "A" weighted)		Weight (net)	8.4 kg, 18.5 lbs.
Phono Input	80 dB	Finish	Silver and Black
Line Level Inputs (RCA)	118 dB		
Line Level Inputs (XLR)	118 dB		
Channel Separation			
Phono Input	> 85 dB		
Line Level Inputs (RCA)	> 85 dB		
Line Level Inputs (XLR)	> 75 dB		

All specifications are accurate at the time of printing.
Rotel reserves the right to make improvements without notice.

www.rotel.com

MQA and the Sound Wave Device are registered trade marks of MQA Limited. © 2016
Being Roon Tested means that Rotel and Roon have collaborated to ensure you
have the best experience using Roon software and the Rotel equipment together, so
you can just enjoy the music.