

RC-1590MKII

STEREO PREAMPLIFIER



ROON
TESTED

Certified
Roon Tested



Supports MQA and
MQA Studio



Balanced XLR
inputs and outputs



Moving Magnet
Phono input for
turntable connection



Wireless
aptX™ and AAC
Bluetooth



Texas Instruments
premium 32-bit/384kHz
Digital to Analog Converter

Reference audio systems deserve reference audio equipment. The Rotel RC-1590MKII is exactly that -- a reference preamplifier rendering analog and digital sources with natural expression in a wide and open sound stage in stunning clarity.

The heart of the RC-1590MKII begins with the power supply featuring dual in-house manufacture toroidal transformers. The transformers are physically and electrically isolated supplying dedicated analog and digital supply voltages to all critical circuits through low ESR slit-foil capacitors eliminating unwanted distortion and an extremely low noise floor.

Digital source inputs are processed utilizing an audiophile grade Texas Instruments 32-bit/384kHz Digital to Audio Converter (DAC) with custom engineered, proprietary acoustically tuned external output filter circuits rendering even the finest details with exceptional clarity and exact positing.

Analog signal paths feature DIRECT-PATH bypass modes eliminating unnecessary circuits maintaining signal integrity and further eliminating unwanted noise and distortion drawing you even closer and immersing you in the music.

The RC-1590MKII supports a full array of inputs ensuring connection to your favorite sources including a Moving Magnet Phono input for vinyl lovers, Analog, Digital, XLR Balanced, high quality aptX™ and AAC wireless Bluetooth, and PC-USB (32-bit/384kHz) supporting MQA unfolding and rendering as well as certified Roon Tested.

Dual RCA and XLR output connection provide the ultimate flexibility including bi-amplification installations. A subwoofer output is also included.

The RC-1590MKII proudly continues Rotel's 60-year legacy and heritage with our ongoing promises of performance, value, and unwavering commitment to quality. Authentic, engaging, and spacious – the RC-1590MKII proudly represents this iconic brand.

RC-1590MKII

STEREO PREAMPLIFIER



SPECIFICATIONS

Total Harmonic Distortion (20 Hz-20k Hz)	< 0.002%	Digital Section	
Intermodulation Distortion (60 Hz : 7k Hz, 4:1)	< 0.002%	Frequency Response	20 Hz - 20k Hz (0 ± 0.5 dB, Max)
Input Sensitivity / Impedance		Signal to Noise Ratio (IHF "A" weighted)	108 dB
Phono Input (MM)	2.5 mV / 47k ohms	Input Sensitivity/Impedance	0 dBFs / 75 ohms
Line Level Inputs (RCA)	150 mV / 100k ohms	Preamplifier Output Level	1.65 V (at - 20 dB)
Line Level Inputs (XLR)	250 mV / 100k ohms	Coaxial/Optical Digital Signals	SPDIF LPCM (up to 24-bit / 192k Hz)
Input Overload		PC-USB	USB Audio Class 1.0 (up to 24-bit / 96k Hz) USB Audio Class 2.0 (up to 32-bit / 384k Hz)* *Driver installation required
Phono Input	64 mV		MQA and MQA Studio (up to 24-bit / 384k Hz)
Line Level Inputs (RCA)	4 V		Roon Tested
Line Level Inputs (XLR)	5.5 V	Power Requirements	
Output Level		Europe	230 V, 50 Hz
Line Level (RCA)	1 V	USA	120 V, 60 Hz
Balance (XLR)	2 V	Power Consumption	45 watts
Frequency Response		Standby Power Consumption	< 0.5 watts
Phono Input	20 Hz-20k Hz (+0.3 dB, -0.2 dB)	BTU	78 BTU/h
Line Level Inputs (RCA)	10 Hz-100k Hz (+0 dB, -0.1 dB)	Dimensions (W x H x D)	431 x 144 x 348 mm 17 x 5 11/16 x 13 7/9 in
Line Level Inputs (XLR)	10 Hz-100k Hz (+0 dB, -0.1 dB)	Front Panel Height	3U / 132.6mm / 5 1/4 in
Tone Controls		Weight (net)	10.1 kg, 22.27 lbs.
Bass	±10 dB at 100 Hz	Finish	Silver and Black
Treble	±10 dB at 10k Hz		
Signal to Noise Ratio (IHF "A" weighted)			
Phono Input	80 dB		
Line Level Inputs (RCA)	117 dB		
Line Level Inputs (XLR)	115 dB		
Channel Separation			
Phono Input	> 85 dB		
Line Level Inputs (RCA)	> 85 dB		
Line Level Inputs (XLR)	> 75 dB		

All specifications are accurate at the time of printing.
Rotel reserves the right to make improvements without notice.

www.rotel.com

MQA and the Sound Wave Device are registered trade marks of MQA Limited. © 2016
Being Roon Tested means that Rotel and Roon have collaborated to ensure you
have the best experience using Roon software and the Rotel equipment together, so
you can just enjoy the music.