

Nagra Streamer



USER MANUAL

P/N 2055440159

All rights reserved - © 2024 rev3

Downloaded from www.linephaze.com

Safety warnings

- Read this manual carefully before operating the Nagra Streamer.
- Should you have any questions on how to setup or use your Streamer, please contact your Nagra dealer.
- Audio Technology Switzerland SA declines any responsibility in the event of an accident caused by the non-observance of these instructions or any other form of user negligence.
- The Streamer is CLASS I equipment. It is essential that it its power supply is connected to a MAINS socket outlet with a protective earthing connection.
- The Streamer must not be exposed to dripping or splashing liquids and no objects filled with liquids, such as vases, should be placed on the machine.
- Never try to open your Streamer to prevent the risk of electric shock and burns. Only Nagra dealers & qualified technicians are allowed to do it for maintenance and specific settings.

Warranty

Audio Technology Switzerland SA certifies that this device has been inspected and tested before leaving the factory. We guarantee our products against all manufacturing defects, for a period of three years for the HD PREAMP, running from the date of delivery to the customer (validated by the serial number on the device casing and the invoice from an official Nagra dealer). This warranty is only valid for the original purchaser of new equipment.

This limited warranty covers the repair and replacement of defective parts, excluding any other remedy.

The absence of a serial number invalidates the warranty. We decline any responsibility for damages resulting directly or indirectly from the use of our products and from the use of any components or spare parts other than those designated as original/approved parts by Audio Technology Switzerland SA. As we constantly strive to improve our products, we reserve the right to modify them or change their specifications without notice.

2

Streamer

Congratulations

Congratulations, you have just purchased one of the best Streamer ever made!

The Streamer was created by an engineering team with more than 70 years of experience designing world-class products for the professional audio, national security and military businesses.

Since its inception in 1951, Nagra has built products that continue to earn a reputation for delivering ultimate sonic performance. Numerous awards have been bestowed upon Nagra for its technical innovation, excellence in design and flawless construction including two Oscars® and two Emmys®.

The professional and Hi-Fi ranges are both designed by our Research and Development department. Nagra has launched a Hi-Fi range to allow the wider public to benefit from technical advances that are often the sole privilege of professionals.

This technology exists in the service of music, your music. We wish you great moments of listening pleasure with your Streamer.

Thank you for your trust.

Package contents

The package of your Streamer includes the following parts:

- One (1) Streamer device chassis
- One (1) user manual
- One (1) power supply and power cord*
- One (1) N-Link fiber optics cable

Please contact your Nagra dealer should anything be missing.

* Depending on your country, the power cord features either a US, European or Swiss plug.

3

Streamer

Downloaded from www.linephaze.com

INSTALLATION OF Streamer

Choosing a location

The Streamer is designed exclusively for indoor use in a moderate climate.


Connection to the Mains

You can use the provided power supply.

To improve the overall performance of your Streamer and your set-up, you can purchase a Nagra Lemo to DC cable and connect the Streamer to either:

- Nagra ACPS III
- Nagra MPS
- Nagra Classic PSU

The Classic PSU will provide the best performance.




4

Streamer

Downloaded from www.linephaze.com

Connection to your network




Connect the Streamer to your network with an Ethernet RJ45 cable.

The Streamer will be configured and controlled via Wifi. Your Wifi and Ethernet ports. have to be connected to the same access point (AP, typically your home router).

Typical home access point provided by your phone or cable company will offer both Wifi and Ethernet plugs.

Connection to a Nagra D/A



Use the N-Link output to connect your Nagra D/A. N-Link is available on the HD DAC X, the TUBE DAC and the Classic DAC II.

5

Streamer


Downloaded from www.linephaze.com

Original HD DAC can be upgraded to "TUBE DAC" level to feature the N-Link.

Other Nagra D/A or third party D/A will connect via the SPDIF output through the RCA connector.

Please note the N-Link will provide a better sound quality as it can play up to DSD 4x (or DSD 256) and it provides an optical isolation between the Streamer and the D/A, meaning it isolates from the computer network as well.

Connection to a non-Nagra D/A



Use SPDIF output to connect to your D/A converter.

Through the SPDIF connection, formats up to 192 kHz 24 bits and DSD (or DSD 64) via "DoP" can be played. You need to configure your source to play these formats. Higher resolution formats will not be compatible and the sound will be muted.

6

Streamer

Downloaded from www.linephaze.com

TIDAL Settings


Within TIDAL App you can detect the Streamer and select it as the output device to stream your music.



Click on the icon

Select Nagra






7

Streamer

Downloaded from www.linephaze.com

Spotify settings


You can play the Streamer directly from the Spotify app. To do so please follow these instructions.



8

Streamer

Downloaded from www.linephaze.com



Streamer

Downloaded from www.linephaze.com

Streamer with Airplay and Airplay 2

Select your Apple Player







10

Streamer

Downloaded from www.linephaze.com

Getting the most of your Nagra Streamer

To get the most of your Streamer, you should use the following apps.

They will allow you to play from major music providers as well as local files from a USB stick or hard drive.

Visit your Apple Store or Google Play Store and download the **Mconnect CONTROL** app.

This app is free of charge and available for phone or tablets.



Please note that this app is provided by a third party called Conversdigital.

The **Mconnect CONTROL** app is designed to work in portrait mode and is compatible with phones and tablets.

If you want to use a tablet exclusively, you may download the **Mconnect CONTROL HD**.


Operating your Streamer

Once the application is installed





Select Play to





Select the Nagra Streamer


12

Streamer

Downloaded from www.linephaze.com

A lot of music

The Nagra Streamer is packed with features that you can access through the **M Connect** app




You can access your Deezer account

vTuner Internet Radio offers thousands of live radio stations from around the world

You can also access your music stored on Dropbox OneDrive iCould Drive

13

Streamer




Select this to access music on your device

This is the USB Stick or HDD connected to your Streamer

This is the storage (NAS) available from your network

Playing files from a USB memory or hard drive


You can play files from a USB key or a USB hard drive. You should connect it here:




14

Streamer

Downloaded from www.linephaze.com





Playing from local files, either from the USB or on the network allows you to listen to high resolution up to DSD 256 (or DSD 4x). This is the best solution to play at the best quality. Please note that DSD 256 needs a N-Link connection to your Nagra D/A converter.


15

Streamer

Downloaded from www.linephaze.com

Qobuz via M Connect

qobuz is working to include the Streamer recognition from its app. Currently you have to use M Connect as a bridge to Qobuz.




16


Streamer

Downloaded from www.linephaze.com

Create a multiroom group



Playback with a group



17

Streamer

Downloaded from www.linephaze.com

Software update

From time to time we issue a new software to make sure your Streamer is always optimal. When a new software is available, the app will display the following message.



you should then click on YES, the following message will pop-up





Once the Streamer has completed the update, it will display the following message:

You should then restart it.

Case cleaning

Clean the Streamer chassis by using a soft, lint-free, slightly damp cloth. Do not use any cleaning products that could have a corrosive effect.

TECHNICAL SPECIFICATIONS

Connections	Network Ethernet RJ45 USB hard drive or memory stick	
Outputs	N-Link for compatible Nagra D/A SPDIF for other D/A (up to 192 kHz, DSD 64 with DOP	
Powering	12V DC, about 0.7 A consumption	
Power consumption	10 W	May increase with a USB HDD
Operating temperature	+15 °C to +35 °C +59 °F to +95 °F	Moderate climate
Operating environment	Indoor only	IP30
Overall dimensions with VFP LxWxH	W x D = 185 x 166 x 41 mm Weight = 1.9 kg (4.1 lbs.)	7.2 x 6.5 x 1.6 inches
Weight (net)	1.9 Kg	4.1 lb

Specifications may change without notice

19

Streamer

Downloaded from www.linephaze.com



Disposal of old electrical & electronic equipment (Applicable in the European Union and other European countries with separate collection systems).

This symbol on the product or on its packaging indicates that it should be handed over to the applicable collection point for the recycling of electrical and electronic equipment. By ensuring this product is disposed of correctly, you will help prevent potential negative consequences for the environment and human health. The recycling of materials will help to conserve natural resources. For more detailed information about recycling of this product, please contact your local authority, your household waste disposal service or the shop where you purchased the product.

Applicable to the following devices: Streamer and all the package contents